



# TRAILMASTER VOLTZ

## **THE ULTIMATE EXTERNAL TRAIL CAMERA BATTERY PACK**

### **CHARGING THE BATTERY:**

Charge the battery before using it in the field with the included 2 amp wall charger. Red light will come on when charging and green light will appear when fully charged. 5 hours to completely charge a dead battery. Built-in battery tester will indicate battery level when product is in use.

**NOTE:** Only use the 12 Volt port to charge the battery. DO NOT USE THE 6 VOLT PORT.

### **SET-UP & INFO:**

There are 2 "battery camera" wires included.

- Bigger plug is a 5.5 x 2.1mm wire compatible with:
  - Spartan GoLive, Spartan GoCam 2, SpyPoint 12V, Moultrie 12V, Covert WC30 12V, Covert WC20 12V, Browning 12V, Stealth Cam 12V.
- Smaller plug is a 4.0 x 1.7mm wire compatible with:
  - Spartan GoCam 6V, Covert Blackhawk 6V, Tactacam Reveal 12V, Wise Eye 12V

**WARNING:** Trailmaster Voltz or any dealer is not responsible for **WRONG VOLTAGE HOOKUPS**. If your camera voltage does not match the correct port voltage (6 or 12) IT WILL FRY YOUR CAMERA.

Trailmaster Voltz battery is a LiFePO4 lithium iron phosphate 12V 10ah 128 watt hour battery, it is known to have an approximate 10 year or 3,000 charge cycle lifespan.

**NOTE:** Try not to leave battery dead for complete off season as it could negatively effect the battery cells.

### **WARRANTY:**

**1 year warranty included.** Keep copy of sales receipt and/or write date of purchase on battery.

**DISCLAIMER:** Warranty void if charged by the 6 VOLT PORT.

**Thank you for choosing Trailmaster Voltz battery pack for your trail camera power needs**

(330) 440-5327 | whdfoodplots@gmail.com | www.whdfoodplots.com